

**Fiber Termination Box(FTB)
Outdoor, 4 fibers
GP31-2P04B**

Installation Manual


GP31-2P04B is a new generation product for fiber to the home(FTTH). The box is light and compact; it is especially for connecting and protection for fiber cable of FTTH.

1. Feature

- Wall mounting;
- Protection grade: IP65 ;
- Design for the installation and application of LC(Deplex)/SC adapter ;
- Design for outdoor cable or indoor drop cable;
- Dimension :208×153×52(mm);
- Maximum 4 cores of LC (double core) / 2 cores of SC ;


2. Internal structure

1	base
2	fixing cable parts
3	Fiber guide and storage
4	adaptor fixing panel
5	splice protective sleeve
6	splice tray
7	cover
8	splice record
9	lock
10	door seal
11	cable gland
12	buckle




3. Operation Instruction:

- 3.1 Open the outer package of box;
- 3.2 Using the key, open the box;



3.3 Introduce cable to the Fixation Kit, strip cable from 120cm below the cable head ,cover with EVA sleeve and insulating tape (sample is the case of outdoor cable inputting) introduce striped cable through adjustable gland, cover with EVA sleeve and fix with ribbon,then fix Core wire ,tighten adjustable gland.




Cable gland

Stainless steel hose hoops

Fiber metal core fixing

3.4 The splice tray can be rotated to horizontal position for easy operation and maintenance. And the splice tray is removable for the splice operation on ground. It is very convenience, as below pictures.



3.5. Mount adapter, insert pigtail; cover inputting pigtail with EVA sleeve, introduce into splice tray, fix by nylon ribbon then cover with splicing sleeve(if there is optical splitter inside ,please follow the indication below:insect into adapter by pigtail after introduced the cable into optical splitter); splice pigtail and inputting fiber together; cover with Shrinkable sleeve and inset into the sleeve slot which is lay on the splice tray, coil fibers on splice tray; coil spare pigtail on the loop at the bottom of the box .



Fiber protective sleeve

Sleeve Holder

Adaptor


Pigtail outlet

3.5.1 Open the screw, install the splitter, and then tight the screw to fix the splitter. (Optional operation)



PLC splitter


3.6 Unload and upload the cover



Please follow this direction(vertical) to upload the cover otherwise cover may be damaged!

4. Install construction

4.1 Drill the 4 holes on the wall for M4 plastic expansion screw as below pictures.;



4.2 Put M4 plastic expansion screws into holes.

4.3 Mounting the box on the wall by 4×30self-tapping screws. Cover the box, and lock it.