

Power Supply

481000C



Power Specifications

	Specification	Remark
Input voltage	85~300V/45~65Hz	TN/TT grounding system
Output voltage	-42-58.5V	Nominal -53.5V
Rectifier power	3000W	LXPower3000/3000M/3000H
Surge current capacity	Nominal 20kA(8/20us), Max.40kA	AC input surge protection
	Nominal 10kA(8/20us), Max.20kA	DC output surge protection

Mechanical Specifications

Parts	Dimension/mm	Weight/kg
Subrack	465x378x400	/
Rectifier module	84x106x242	2.4
Monitor	85x230x42.5	0.8
Battery chamber	/	/
Mounting	600*600*2200	/



Overview

The LXPower481000C is specially designed to meet the demand for compact, flexible, high performance, high reliability power supply. The system consists of 1-20 units LXPower483000 high/standard efficiency rectifier modules of their mixture, a LX2000 monitor module, AC/DC distributors. Adapt to ground mounting.

Features

- Cabinet type design
- Customized size available upon request
- Easy maintenance: hot plug rectifier module and fully front-access maintenance system for wall against or corner mounting
- Advanced battery management improves battery lifespan, especially suitable for poor AC mains application
- Extreme wide input voltage: 85V~300V AC
- Extreme wide operation temperature: -30°C~+65°C
- High/standard efficiency rectifier modules are compatible
- 6U height compact design
- System rated capacity: -53.5V DC/1000A
- Whole monitor ports, RS232/485/SNMP, dry contactors
- LCD display with a state-of-the-art interface allows simple and convenient local set up, control and remote monitor
- Design standards: IEC/EN60950

Applications

- Macro/micro BTS sites
- GSM-R
- Enterprise
- Broadband access
- Optical fiber transmission system

Operation Ambient

Item	Specification	Remark
Storage temperature	-40~+70°C	/
Operation temperature	-30~+65°C	/
Safety	/	according to EN60950 and IEC60950
Communication	RS232+dry contact+SNMP	Non-condensing
Operation moisture	10~95%	/

System Configuration

Model	DC Capacity	Rectifiers	Monitor	Battery Access
LXPower481000C	48V/1000A	1~20 units	LX2000	1~2 strings

Distribution

	LXPower481000C	Remark
AC input	100A/3P*2	/
Battery	500A*2	/
DC output	160A*5+63A*3	LLVD standard configuration
/	100A*6	BLVD standard configuration



Part Details

