

Power Supply

4890S



Power Specifications

	Specification	Remark
Input voltage	85~300V/45~65Hz	TN/TT grounding system
Output voltage	-42-58.5V	Nominal -53.5V
Rectifier power	1800W	LXPower1800/1800M/1800H
Surge current capacity	Nominal 20kA(8/20us), Max.40kA	AC input surge protection
	/	/

Mechanical Specifications

Parts	Dimension/mm	Weight/kg
Subrack	3Ux482.6x378	/
Rectifier module	40.5x106x298.5	1.7
Monitor	42.5x85x230	0.8
Battery chamber	/	/
Mounting	19" rack	/



Overview

The LXPower4890S is specially designed to meet the demand for compact, flexible, high performance, high reliability power supply. The system consists of 1-3 units LXPower1800 high/standard efficiency rectifier modules of their mixture, a LX2000 monitor module, AC/DC distributors. 19 inches and 3U height standard structure adapts to various telecom cabinets and racks.

Features

- Cost effective solution: high integrated power supply including rectifier modules, controller, lightning protection, distributions
- Easy maintenance: hot plug rectifier module and fully front-access maintenance system for wall against or corner mounting
- Advanced battery management improves battery lifespan, especially suitable for poor AC mains application
- Extreme wide input voltage: 85V~300V AC
- Extreme wide operation temperature: -30℃~+65℃
- High/standard efficiency rectifier modules are compatible
- 3U height compact design
- System rated capacity: -53.5V DC/90A
- Whole monitor ports, RS232/485/SNMP, dry contactors
- LCD display with a state-of-the-art interface allows simple and convenient local set up, control and remote monitor
- Design standards: IEC/EN60950

Applications

- Macro/micro BTS sites
- GSM-R
- Enterprise
- Broadband access
- Optical fiber transmission system

Operation Ambient

Item	Specification	Remark
Storage temperature	-40~+70℃	/
Operation temperature	-30~+65℃	/
Safety	/	According to EN60950 and IEC60950
Communication	RS232+dry contact+SNMP	/
Operation moisture	10~95%	Non-condensing

System Configuration

Model	DC Capacity	Rectifiers	Monitor	Battery Access
LXPower4890S	48V/90A	1~3 units	LX2000	1 string

Distribution

/	LXPower4890S	Remark
AC input	32A/2P*1	/
Battery	63A/1P*1	/
DC output	16A/1P*2+32A/1P*3	LLVD standard configuration
/	16A/1P*2+10A/1P*1	BLVD standard configuration



Part Details

